

## FV 7250/7360/7500 EMERGENCY POWER AMPLIFIERS



**EN54-16**

### FEATURES

- ▶ Power amplifiers of VF 7000 PA/VA system.
- ▶ Amplifier model should be selected in accordance to powers, numbers and impedances of speakers.
- ▶ Some features of the device may be disabled when used for other purposes.

### TECHNICAL SPECIFICATIONS

- ▶ Amplifier output power:  
VF 7250: 250W / 100 V  
VF 7360: 360W / 100 V  
VF 7500: 500W / 100 V
- ▶ Signal input 100 mV (Max 1V)
- ▶ Led vumeter.
- ▶ DC protection for speakers.
- ▶ Output short circuit protection.
- ▶ With line transformer (100 volts).
- ▶ Voice alarm input and control.
- ▶ AC / DC Input: AC 220 V 50 Hz. / DC 24 V
- ▶ Mounting: Suitable for 19" Rack Cabinet Standard
- ▶ Dimensions: 440 x 300 x 90 (mm)
- ▶ Weight:  
VF 7250: 12 kg  
VF 7360: 13 kg  
VF 7500: 17.5 kg