

FF SYN1LN INTELLIGENT FIRE ALARM PANEL



EN54-2 EN54-4

FEATURES

- ▶ 1 loop version
- ▶ 0,16,48 and 96 zones indicators
- ▶ 2 programmable sounder output
- ▶ 4A power supply in accordance with EN54/4
- ▶ Large graphical display
- ▶ Help and alarm warning screens
- ▶ 2 programmable function keys
- ▶ 3 programmable front panel LED
- ▶ Printer (optional)

TECHNICAL SPECIFICATIONS

Screen	260×64 LCD
2 Siren Circuit	1A
Fire Contact	1A 30V DC
System	5A
Home Network	20mm 3A
Operating Temp..	-5°C +50°C
Humidity	%95
Main Supply Volt.	230 VAC

ORDER DETAILS

- ▶ FF SYN1LN Intelligent Fire Alarm Panel
- ▶ FF SYN4L Intelligent Fire Alarm Panel
- ▶ FF SYN2L Intelligent Fire Alarm Panel
- ▶ FF SYN1L Intelligent Fire Alarm Panel
- ▶ FF K555 Network Card